

# GSM CAMERA



( Bracket is Built )

## MAIN FEATURES

**0.3 M Px Color CMOS**  
**Linked with Wireless Alarm Sensors**  
**MMS Pictures on Mobile/ SMS Controls**  
**Built-in Voice Surveillance**  
**Multi Alarms via SMS/MMS/Email/Call**

MODEL **CVW900A**

**GSM Remote Alarm Camera**

## Applications

The V9001B is light and portable, It uses only a sim card, that can be activated along side your existing mobile phone.

If the GSM camera detects motion it will automatically send a text message to your mobile phone followed by a picture message of the area in view. So you can keep up with everything going on.

If required, it can send messages to as many as 10 mobiles as well as to your email address. The camera will also act as a microphone allowing you to call and listen in.

## Technical Specifications

<b>Image Resolutions</b>	0.3 M Pixels CMOS
<b>Effective Pixels</b>	640x480/ 320x240/ 160x128
<b>infra-red LEDs</b>	8 PCs
<b>Image Format</b>	JPEG
<b>Viewing Angle</b>	60° (Hor) / 60° (Ver)
<b>Best Shooting Distance</b>	< 6 Meter at Night
<b>Operating Frequencies</b>	EGSM 900/ DCS 1800 Optional GSM 850/ PCS 1900
<b>Communication Protocols</b>	GSM Phase 2/2+
<b>Max. Sensors</b>	15 Units
<b>Eff Sensor Distance</b>	6 Meters
<b>Wireless Sensor Code</b>	ASK
<b>Wireless Sensor Freq.</b>	315 / 413 Mhz
<b>Sensor Baud Rate</b>	500-2500 bps
<b>Remote Control Range</b>	50 M
<b>Operating Temp.</b>	-10° - 45°
<b>Storage Temp.</b>	-20° - 60°
<b>Relative Humidity</b>	10-90%
<b>Battery Capacity</b>	800 mAH
<b>Eff. Working Hour</b>	24 Hours / Standby
<b>Power Adaptor</b>	5.5 Vdc / 1A



**chivar**

www.chivar.com



The specification is subject to changes without notice.  
Chivar is the registered trade mark of Bestchoice International Co., Ltd.