

GSM CAMERA



(Bracket is Built)

MAIN FEATURES

0.3 M Px Color CMOS
Linked with Wireless Alarm Sensors
MMS Pictures on Mobile/ SMS Controls
Built-in Voice Surveillance
Multi Alarms via SMS/MMS/Email/Call
Motion-Detection Sensor

MODEL **CVW901B**

GSM Remote Alarm Camera

Applications

The V9001B is light and portable, It uses only a sim card, that can be activated along side your existing mobile phone.

If the GSM camera detects motion it will automatically send a text message to your mobile phone followed by a picture message of the area in view. So you can keep up with everything going on.

If required, it can send messages to as many as 10 mobiles as well as to your email address. The camera will also act as a microphone allowing you to call and listen in.

Technical Specifications

Image Resolutions	0.3 M Pixels CMOS
Effective Pixels	640x480/ 320x240/ 160x128
infra-red LEDs	8 PCs
Image Format	JPEG
Viewing Angle	60° (Hor) / 60° (Ver)
Best Shooting Distance	< 6 Meter at Night
Operating Frequencies	EGSM 900/ DCS 1800 Optional GSM 850/ PCS 1900
Communication Protocols	GSM Phase 2/2+
Max. Sensors	15 Units
Eff Sensor Distance	6 Meters
Wireless Sensor Code	ASK
Wireless Sensor Freq.	315 / 413 Mhz
Sensor Baud Rate	500-2500 bps
Remote Control Range	50 M
Operating Temp.	-10° - 45°
Storage Temp.	-20° - 60°
Relative Humidity	10-90%
Battery Capacity	800 mAH
Eff. Working Hour	24 Hours / Standby
Power Adaptor	5.5 Vdc / 1A



chivar

www.chivar.com



The specification is subject to changes without notice.
Chivar is the registered trade mark of Bestchoice International Co., Ltd.