

# CCTV CAMERA



## MAIN FEATURES

**1/4" Wireless Color CMOS  
Wireless DVR Receiver  
Built-in 2.5" Display with Audio  
Motion-Detection Record  
Support SD Cards Up to 32GB**

**MODEL CVRS825D**

**Baby-Monitor Camera / Recorder**

## Application

Small-size wireless camera and display-built-in recorder makes it very easy for everyone to use.

This camera set can be used to see your little baby.

## Notes

Channel 1 - 2,414 Mhz  
Channel 2 - 2,432 Mhz  
Channel 3 - 2,450 Mhz  
Channel 4 - 2,468 Mhz

## Technical Specifications

<b>Chip Type</b>	1/4" Pinhole Color CMOS
<b>Horizonatl Scan</b>	380 TV Lines
<b>Effective Resolutions</b>	640x480/ 320 x 240/ 160x128
<b>Lens</b>	3.6 mm, Built-in Mic.
<b>Synchronization</b>	Internal
<b>Frequency</b>	2.4 GHZ, 4 Channel, Selectable
<b>Power Adapter</b>	5Vdc / 1A
<b>Dimensions</b>	17(W) x 17(H) x 65 mm
<b>Camera Weight</b>	20 gm
<b>Recorder</b>	
<b>Recording Format</b>	AVI/ jPEG
<b>Display</b>	2.5" Built-in
<b>Video Input</b>	4 Channels/ Wireless
<b>Video Output</b>	1 Vp-p, 60 Ohms RCA
<b>Serial Bus</b>	USB 2.0/ USB OTG 1.1
<b>Disk File Format</b>	FAT-32
<b>Audio Output</b>	Yes
<b>Memory Capacity</b>	32 GB
<b>Video Record Time</b>	10 sec/ Clip
<b>Operating Temperatures</b>	-10° - 40° C
<b>Storage Temperatures</b>	-30° - 60° C
<b>Power Adapter</b>	5 Vdc / 1 A
<b>Dimensions</b>	65(W) x 140(L) x 20 mm
<b>Receiver Weight</b>	140 gm



**chivar**

www.chivar.com



The specification is subject to changes without notice.  
Chivar is the registered trade mark of Bestchoice International Co., Ltd.