

# WIRELESS TRANSCEIVER



## MAIN FEATURES

**2.4 Ghz High-Power  
1.2 Watts  
4 Selectable Channels  
Upto 230 Meter Distance\***

MODEL **CVT1000-24** **High-Power Wireless A/V Transceiver**

## Application

Wireless A/V Transmitter/ Receiver. 2.4G frequency and strong anti-interference capacity  
Up to 4 channels for selection and minimal interference between different channels  
Full aluminum enclosure providing enhanced radiation  
1,200 mW transmitting power up to 120-230 meters distance\*

## Technical Specifications

<b>Working Frequencies</b>	2,350 - 2,550 Mhz
<b>Available Channels</b>	4
<b>Transmit Component</b>	Dual-Track Visual/Audio Signals
<b>Visual Signal Format</b>	PAL/ NTSC
<b>Audio Input Impedance</b>	1k $\Omega$ , 1Vp-p
<b>Visual Input Impedance</b>	75 $\Omega$ , 1Vp-p
<b>Power Supply</b>	DC 9 V/ 2.5 W
<b>Transmit Power</b>	1,000 mW
<b>Expected Distance</b>	230 meters
<b>Package Dimensions</b>	230X200X70mm
<b>Package Weight</b>	0.8 Kgs

\*Distance varies according to many factors including antenna types and line of sight



**chivar**

www.chivar.com



The specification is subject to changes without notice.  
Chivar is the registered trade mark of Bestchoice International Co., Ltd.